

Fortinet

Exam Questions NSE7_EFW-7.0

Fortinet NSE 7 - Enterprise Firewall 7.0



NEW QUESTION 1

When using the SSL certificate inspection method to inspect HTTPS traffic, how does FortiGate filter web requests when the client browser does not provide the server name indication (SNI) extension?

- A. FortiGate uses the requested URL from the user's web browser.
- B. FortiGate uses the CN information from the Subject field in the server certificate.
- C. FortiGate blocks the request without any further inspection.
- D. FortiGate switches to the full SSL inspection method to decrypt the data.

Answer: B

NEW QUESTION 2

Refer to the exhibit, which shows the output of a debug command.

```
FGT # get router info ospf interface port4
port4 is up, line protocol is up
  Internet Address 172.20.121.236/24, Area 0.0.0.0, MTU 1500
  Process ID 0, Router ID 0.0.0.4, Network Type BROADCAST, Cost: 1
  Transmit Delay is 1 sec, State DROther, Priority 1
  Designated Router (ID) 172.20.140.2, Interface Address 172.20.121.2
  Backup Designated Router (ID) 0.0.0.1, Interface Address 172.20.121.239
  Timer intervals configured, Hello 10.000, Dead 40, Wait 40, Retransmit 5
    Hello due in 00:00:05
  Neighbor Count is 4, Adjacent neighbor count is 2
  Crypt Sequence Number is 411
  Hello received 106 send 27, DD received 6 sent 3
  LS-Req received 2 sent 2, LS-Upd received 7 sent 17
  LS-Ack received 4 sent 3, Discarded 1
```

Which two statements about the output are true? (Choose two.)

- A. The local FortiGate OSPF router ID is 0.0.0.4.
- B. Port4 is connected to the OSPF backbone area.
- C. In the network connected to port4, two OSPF routers are down.
- D. The local FortiGate is the backup designated router.

Answer: AB

Explanation:

Area 0.0.0.0 is the backbone area.

NEW QUESTION 3

Refer to the exhibit, which contains partial outputs from two routing debug commands.

```
FortiGate # get router info routing-table database

S    0.0.0.0/0 [20/0] via 100.64.2.254, port2, [10/0]
S    *>0.0.0.0/0 [10/0] via 100.64.1.254, port1

FortiGate # get router info routing-table all

S*   0.0.0.0/0 [10/0] via 100.64.1.254, port1
```

Why is the port2 default route not in the second command's output?

- A. It has a higher priority value than the default route using port1.
- B. It is disabled in the FortiGate configuration.
- C. It has a lower priority value than the default route using port1.
- D. It has a higher distance than the default route using port1.

Answer: D

NEW QUESTION 4

Examine the partial output from the IKE real time debug shown in the exhibit; then answer the question below.

```
#diagnose debug application ike -1
#diagnose debug enable
ike 0: .....: 75: responder: aggressive mode get 1st message...
...
ike 0: .....:76: incoming proposal:
ike 0: .....:76: proposal id = 0:
ike 0: .....:76:  protocol id= ISAKMP:
ike 0: .....:76:  trans_id = KEY_IKE.
ike 0: .....:76:  encapsulation = IKE/none
ike 0: .....:76:  type= OAKLEY_ENCRYPT_ALG, val=AES_CBC.
ike 0: .....:76:  type= OAKLEY_HASH_ALG, val=SHA2_256.
ike 0: .....:76:  type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0: .....:76:  type=OAKLEY_GROUP, val=MODP2048.
ike 0: .....:76: ISAKMP SA lifetime=86400
ike 0: .....:76: my proposal, gw Remote:
ike 0: .....:76: proposal id=1:
ike 0: .....:76:  protocol id= ISAKMP:
ike 0: .....:76:  trans_id= KEY_IKE.
ike 0: .....:76:  encapsulation = IKE/none
ike 0: .....:76:  type=OAKLEY_ENCRYPT_ALG, val=DES_CBC.
ike 0: .....:76:  type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0: .....:76:  type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0: .....:76:  type=OAKLEY_GROUP, val=MODP2048.
ike 0: .....:76: ISAKMP SA lifetime=86400
ike 0: .....:76: proposal id=1:
ike 0: .....:76:  protocol id= ISAKMP:
ike 0: .....:76:  trans_id= KEY_IKE.
ike 0: .....:76:  encapsulation = IKE/none
ike 0: .....:76:  type=OAKLEY_ENCRYPT_ALG, val=DES_CBC.
ike 0: .....:76:  type= OAKLEY_HASH_ALG, val=SHA2_256.
ike 0: .....:76:  type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0: .....:76:  type=OAKLEY_GROUP, val=MODP1536.
ike 0: .....:76: ISAKMP SA lifetime=86400
ike 0: .....:76: negotiation failure
ike Negotiate ISAKMP SA Error: ike 0: .....:76: no SA proposal chosen
```

Why didn't the tunnel come up?

- A. IKE mode configuration is not enabled in the remote IPsec gateway.
- B. The remote gateway's Phase-2 configuration does not match the local gateway's phase-2 configuration.
- C. The remote gateway's Phase-1 configuration does not match the local gateway's phase-1 configuration.
- D. One IPsec gateway is using main mode, while the other IPsec gateway is using aggressive mode.

Answer: C

NEW QUESTION 5

View the exhibit, which contains the partial output of an IKE real-time debug, and then answer the question below.


```
ike 0:9268ab9dea63aa3/0000000000000000:591: responder: main mode get 1st message...
ike 0:9268ab9dea63aa3/0000000000000000:591: incoming proposal:
ike 0:9268ab9dea63aa3/0000000000000000:591: proposal id = 0:
ike 0:9268ab9dea63aa3/0000000000000000:591: protocol id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: trans_id = KEY IKE.
ike 0:9268ab9dea63aa3/0000000000000000:591: encapsulation = IKE/none
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_ENCRYPT_ALG, val=3DES_CBC.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_GROUP, val=MODP1536.
ike 0:9268ab9dea63aa3/0000000000000000:591: ISAKMP SA lifetime=86400
ike 0:9268ab9dea63aa3/0000000000000000:591: proposal id=0:
ike 0:9268ab9dea63aa3/0000000000000000:591: protocol id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: trans_id = KEY IKE.
ike 0:9268ab9dea63aa3/0000000000000000:591: encapsulation = IKE/none
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_ENCRYPT_ALG, val=3DES_CBC.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_GROUP, val=MODP1536.
ike 0:9268ab9dea63aa3/0000000000000000:591: ISA KMP SA lifetime=86400
ike 0:9268ab9dea63aa3/0000000000000000:591: my proposal, gw VPN:
ike 0:9268ab9dea63aa3/0000000000000000:591: proposal id = 1:
ike 0:9268ab9dea63aa3/0000000000000000:591: protocol id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: trans_id = KEY IKE.
ike 0:9268ab9dea63aa3/0000000000000000:591: encapsulation = IKE/none
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_ENCRYPT_ALG, val=AES_CBC,
key-len=128
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_HASH_ALG, val=SHA2_512.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_GROUP, val=MODP2048.
ike 0:9268ab9dea63aa3/0000000000000000:591: ISAKMP SA lifetime=86400
ike 0:9268ab9dea63aa3/0000000000000000:591: proposal id = 1:
ike 0:9268ab9dea63aa3/0000000000000000:591: protocol id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: trans_id = KEY IKE.
ike 0:9268ab9dea63aa3/0000000000000000:591: encapsulation = IKE/none
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_ENCRYPT_ALG, val=AES_CBC,
key-len=128
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_HASH_ALG, val=SHA2_512.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_GROUP, val=MODP2048.
ike 0:9268ab9dea63aa3/0000000000000000:591: ISAKMP SA lifetime=86400
ike 0:9268ab9dea63aa3/0000000000000000:591: proposal id = 1:
ike 0:9268ab9dea63aa3/0000000000000000:591: protocol id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: trans_id = ISAKMP:
ike 0:9268ab9dea63aa3/0000000000000000:591: encapsulation = IKE/none
ike 0:9268ab9dea63aa3/0000000000000000:591: type= OAKLEY_ENCRYPT_ALG, val =AES-CBC,
key-len=128
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_HASH_ALG, val=SHA2_512.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:9268ab9dea63aa3/0000000000000000:591: type=OAKLEY_GROUP, val=MODP1536.
ike 0:9268ab9dea63aa3/0000000000000000:591: ISAKMP SA lifetime=86400
```

The administrator does not have access to the remote gateway. Based on the debug output, what configuration changes can the administrator make to the local gateway to resolve the phase 1 negotiation error?

- A. Change phase 1 encryption to 3DES and authentication to SHA128.
- B. Change phase 1 encryption to AES128 and authentication to SHA512.
- C. Change phase 1 encryption to AESCBC and authentication to SHA2.
- D. Change phase 1 encryption to AES256 and authentication to SHA256.

Answer: D

NEW QUESTION 6

Refer to the exhibit, which contains the output of get system ha status. Which two statements about the output are true? (Choose two.)

```
NGFW-1 # get system ha status
HA Health Status: OK
Model: FortiGate-VM64
Mode: HA A-P
Group: 2
Debug: 0
Cluster Uptime: 0 days 4:23:19
Cluster state change time: 2019-01-25 10:19:46
Master selected using:
  <2019/01/25 10:19:46> FGV010000077649 is selected as the master because it has the largest value
of override priority.
  <2019/01/25 10:19:40> FGV010000077649 is selected as the master because it's the only member in
the cluster.
ses_pickup: disable
override: enable
Configuration Status:
  FGV010000077649 (updated 1 seconds ago): in-sync
  FGV010000077650 (updated 0 seconds ago): out-of-sync
System Usage stats:
  FGV010000077649 (updated 1 seconds ago):
    sessions=27, average-cpu-user/nice/system/idle=1%/0%/0%/99%, memory=56%
  FGV010000077650 (updated 0 seconds ago):
    sessions=2, average-cpu-user/nice/system/idle=1%/0%/0%/99%, memory=57%
HBDEV stats:
  FGV010000077649 (updated 1 seconds ago):
    port7: physical/10000full, up, rx-bytes/packets/dropped/errors=63817615/202024/0/0, tx=
71110281/121109/0/0
  FGV010000077650 (updated 0 seconds ago):
    port7: physical/10000full, up, rx-bytes/packets/dropped/errors=79469596/122024/0/0, tx=
30877890/107878/0/0
Master: NGFW-1      , FGV010000077649, cluster index = 1
Slave : NGFW-2      , FGV010000077650, cluster index = 0
number of voluster: 1
voluster 1: work 169.254.0.2
Master: FGV010000077649, operating cluster index = 0
Slave : FGV010000077650, operating cluster index = 1
```

- A. The slave configuration is synchronized with the master.
- B. port7 is used as the HA heartbeat on all devices in the cluster.
- C. Primary is selected based on the priority configured under config system ha.
- D. The HA management IP is 169.254.0.2.

Answer: BC

NEW QUESTION 7

What does the dirty flag mean in a FortiGate session?

- A. Traffic has been blocked by the antivirus inspection.
- B. The next packet must be re-evaluated against the firewall policies.
- C. The session must be removed from the former primary unit after an HA failover.
- D. Traffic has been identified as from an application that is not allowed.

Answer: B

Explanation:

<https://kb.fortinet.com/kb/viewContent.do?externalId=FD40119&sliceId=1>

NEW QUESTION 8

View the exhibit, which contains the output of diagnose sys session stat, and then answer the question below.

```
NGFW-1 # diagnose sys session stat
misc info:      session_count=591  setup_rate=0  exp_count=0
clash=162  memory_tension_drop=0  ephemeral=0/65536
removeable=0
delete=0, flush=0, dev_down=0/0
TCP sessions:
    166 in NONE state
    1 in ESTABLISHED state
    3 in SYN_SENT state
    2 in TIME_WAIT state
firewall error stat:
error1=00000000
error2=00000000
error3=00000000
error4=00000000
tt=00000000
cont=00000000
ids_recv=00000000
url_recv=00000000
av_recv=00000000
fqdn_count=00000006
global: ses_limit=0  ses6_limit=0  rt_limit=0  rt6_limit=0
```

Which statements are correct regarding the output shown? (Choose two.)

- A. There are 0 ephemeral sessions.
- B. All the sessions in the session table are TCP sessions.
- C. No sessions have been deleted because of memory pages exhaustion.
- D. There are 166 TCP sessions waiting to complete the three-way handshake.

Answer: AC

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=FD40578>

NEW QUESTION 9

Which statements about bulk configuration changes using FortiManager CLI scripts are correct? (Choose two.)

- A. When executed on the Policy Package, ADOM database, changes are applied directly to the managed FortiGate.
- B. When executed on the Device Database, you must use the installation wizard to apply the changes to the managed FortiGate.
- C. When executed on the All FortiGate in ADOM, changes are automatically installed without creating a new revision history.
- D. When executed on the Remote FortiGate directly, administrators do not have the option to review the changes prior to installation.

Answer: BD

Explanation:

CLI scripts can be run in three different ways: Device Database: By default, a script is executed on the device database. It is recommend you run the changes on the device database (default setting), as this allows you to check what configuration changes you will send to the managed device. Once scripts are run on the device database, you can install these changes to a managed device using the installation wizard.

Policy Package, ADOM database: If a script contains changes related to ADOM level objects and policies, you can change the default selection to run on Policy Package, ADOM database and can then be installed using the installation wizard.

Remote FortiGate directly (through CLI): A script can be executed directly on the device and you don't need to install these changes using the installation wizard. As the changes are directly installed on the managed device, no option is provided to verify and check the configuration changes through FortiManager prior to executing it.

NEW QUESTION 10

Refer to the exhibit, which contains partial output from an IKE real-time debug.


```
ike 0: comes 10.0.0.2:500->10.0.0.1:500, ifindex=7. . .
ike 0: IKEv2 exchange=Aggressive id=a2fbd6bb6394401a/06b89c022d4df682 len=426
ike 0: Remotesite:3: initiator: aggressive mode get 1st response. . .
ike 0: Remotesite:3: VID DPD AFCAD71368A1F1C96B8696FC77570100
ike 0: Remotesite:3: DPD negotiated
ike 0: Remotesite:3: VID FORTIGATE 8299031757A36082C6A621DE00000000
ike 0: Remotesite:3: peer is FortiGate/PortiOS (v0 b0)
ike 0: Remotesite:3: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3
ike 0: Remotesite:3: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3C0000000
ike 0: Remotesite:3: received peer identifier PQDN 'remote'
ike 0: Remotesite:3: negotiation result
ike 0: Remotesite:3: proposal id = 1:
ike 0: Remotesite:3:   protocol id = ISAKMP:
ike 0: Remotesite:3:   trans_id = KEY_IKE.
ike 0: Remotesite:3:   encapsulation = IKE/none.
ike 0: Remotesite:3:   type=OAKLEY_ENCRYPT_ALG, val=AES_CBC, key-len=128
ike 0: Remotesite:3:   type=OAKLEY_HASH_ALG, val=SHA.
ike 0: Remotesite:3:   type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0: Remotesite:3:   type=OAKLEY_GROUP, val=MODP1024.
ike 0: Remotesite:3: ISAKMP SA lifetime=86400
ike 0: Remotesite:3: NAT-T unavailable
ike 0: Remotesite:3: ISAKMP SA a2fbd6bb6394401a/06b89c022d4df682 key
16:39915120ED73ED73E520787C801DE3678916
ike 0: Remotesite:3: PSK authentication succeeded
ike 0: Remotesite:3: authentication OK
ike 0: Remotesite:3: add INITIAL-CONTACT
ike 0: Remotesite:3: enc
A2FBD6BB6394401A06B89C022D4DF6820810040100000000000000500B000018882A07BE09026CA8B2
ike 0: Remotesite:3: out
A2FBD6BB6394401A06B89C022D4DF6820810040100000000000005C64D5CBA90B873F150CB8B5CC2A
ike 0: Remotesite:3: sent IKE msg (agg_i2send): 10.0.0.1:500->10.0.0.2:500, len=140,
id=a2fbd6bb6394401a/
ike 0: Remotesite:3: established IKE SA a2fbd6bb6394401a/06b89c022d4df682
```

Which two statements about this debug output are correct? (Choose two.)

- A. The remote gateway IP address is 10.0.0.1.
- B. The initiator provided remote as its IPsec peer ID.
- C. It shows a phase 1 negotiation.
- D. The negotiation is using AES128 encryption with CBC hash.

Answer: BC

NEW QUESTION 10

Which of the following conditions must be met for a static route to be active in the routing table? (Choose three.)

- A. The next-hop IP address is up.
- B. There is no other route, to the same destination, with a higher distance.
- C. The link health monitor (if configured) is up.
- D. The next-hop IP address belongs to one of the outgoing interface subnets.
- E. The outgoing interface is up.

Answer: CDE

Explanation:

A configured static route only goes to routing table from routing database when all the following are met :

- > The outgoing interface is up
- > There is no other matching route with a lower distance
- > The link health monitor (if configured) is successful
- > The next-hop IP address belongs to one of the outgoing interface subnets

NEW QUESTION 14

How does FortiManager handle FortiGuard requests from FortiGate devices, when it is configured as a local FDS?

- A. FortiManager can download and maintain local copies of FortiGuard databases.
- B. FortiManager supports only FortiGuard push to managed devices.
- C. FortiManager will respond to update requests only if they originate from a managed device.
- D. FortiManager does not support rating requests.

Answer: A

NEW QUESTION 16

Examine the output of the 'diagnose sys session list expectation' command shown in the exhibit; than answer the question below.

```
#diagnose sys session list expectation

session info: proto= proto_state=0 0 duration=3 expire=26 timeout=3600
flags=00000000
sockflag=00000000 sockport=0 av_idx=0 use=3
origin-shaper=
reply-shaper=
per-ip_shaper=
ha_id=0 policy_dir=1 tunnel=/
state=new complex
statistic (bytes/packets/allow_err): org=0/0/0 reply=0/0/0 tuples=2
orgin-> sink: org pre-> post, reply pre->post dev=2->4/4->2
gwy=10.0.1.10/10.200.1.254
hook=pre dir=org act=dnat 10.171.121.38:0-> 10.200.1.1: 60426
(10.0.1.10: 50365)
hook= pre dir=org act=noop 0.0.0.0:0-> 0.0.0.0:0 (0.0.0.0:0)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
seriall=0000000e9 tos=ff/ff ips_view=0 app_list=0 app=0
dd type=0 dd_mode=0
```

Which statement is true regarding the session in the exhibit?

- A. It was created by the FortiGate kernel to allow push updates from FortiGuard.
- B. It is for management traffic terminating at the FortiGate.
- C. It is for traffic originated from the FortiGate.
- D. It was created by a session helper or ALG.

Answer: D

NEW QUESTION 21

Which the following events can trigger the election of a new primary unit in a HA cluster? (Choose two.)

- A. Primary unit stops sending HA heartbeat keepalives.
- B. The FortiGuard license for the primary unit is updated.
- C. One of the monitored interfaces in the primary unit is disconnected.
- D. A secondary unit is removed from the HA cluster.

Answer: AC

NEW QUESTION 24

Two independent FortiGate HA clusters are connected to the same broadcast domain. The administrator has reported that both clusters are using the same HA virtual MAC address. This creates a duplicated MAC address problem in the network. What HA setting must be changed in one of the HA clusters to fix the problem?

- A. Group ID.
- B. Group name.
- C. Session pickup.
- D. Gratuitous ARPs.

Answer: A

Explanation:

https://help.fortinet.com/fos50hlp/54/Content/FortiOS/fortigate-high-availability-52/HA_failoverVMAC.htm

NEW QUESTION 26

Examine the IPsec configuration shown in the exhibit; then answer the question below.

Name	<input type="text" value="Remote"/>
Comments	<input type="text" value="Comments"/>
Network	
IP Version	<input checked="" type="radio"/> IPv4 <input type="radio"/> IPv6
Remote Gateway	<input type="text" value="Static IP Address"/> <input checked="" type="checkbox"/>
IP Address	<input type="text" value="10.0.10.1"/>
Interface	<input type="text" value="port1"/> <input checked="" type="checkbox"/>
Mode Config	<input type="checkbox"/>
NAT Traversal	<input checked="" type="checkbox"/>
Keepalive Frequency	<input type="text" value="10"/>
Dead Peer Detection	<input checked="" type="checkbox"/>

An administrator wants to monitor the VPN by enabling the IKE real time debug using these commands: diagnose vpn ike log-filter src-addr4 10.0.10.1
diagnose debug application ike -1 diagnose debug enable

The VPN is currently up, there is no traffic crossing the tunnel and DPD packets are being interchanged between both IPsec gateways. However, the IKE real time debug does NOT show any output. Why isn't there any output?

- A. The IKE real time shows the phases 1 and 2 negotiations onl
- B. It does not show any more output once the tunnel is up.
- C. The log-filter setting is set incorrectl
- D. The VPN's traffic does not match this filter.
- E. The IKE real time debug shows the phase 1 negotiation onl
- F. For information after that, the administrator must use the IPsec real time debug instead: diagnose debug application ipsec -1.
- G. The IKE real time debug shows error messages onl
- H. If it does not provide any output, it indicates that the tunnel is operating normally.

Answer: B

NEW QUESTION 30

An administrator has enabled HA session synchronization in a HA cluster with two members. Which flag is added to a primary unit's session to indicate that it has been synchronized to the secondary unit?

- A. redir.
- B. dirty.
- C. synced
- D. nds.

Answer: C

Explanation:

The synced sessions have the 'synced' flag. The command 'diag sys session list' can be used to see the sessions on the member, with the associated flags.

NEW QUESTION 32

Which statement about memory conserve mode is true?

- A. A FortiGate exits conserve mode when the configured memory use threshold reaches yellow.
- B. A FortiGate starts dropping all the new and old sessions when the configured memory use threshold reaches extreme.
- C. A FortiGate starts dropping new sessions when the configured memory use threshold reaches red
- D. A FortiGate enters conserve mode when the configured memory use threshold reaches red

Answer: D

NEW QUESTION 34

Which two tasks are automated using the Install Wizard on FortiManager? (Choose two.)

- A. Preview pending configuration changes for managed devices.
- B. Add devices to FortiManager.
- C. Import policy packages from managed devices.
- D. Install configuration changes to managed devices.
- E. Import interface mappings from managed devices.

Answer: AD

Explanation:

https://help.fortinet.com/fmgr/50hlp/56/5-6-2/FortiManager_Admin_Guide/1000_Device%20Manager/1200_ins

There are 4 main wizards: Add Device: is used to add devices to central management and import their configurations.

Install: is used to install configuration changes from Device Manager or Policies & Objects to the managed devices. It allows you to preview the changes and, if the administrator doesn't agree with the changes, cancel and modify them.

Import policy: is used to import interface mapping, policy database, and objects associated with the managed devices into a policy package under the Policy & Object tab. It runs with the Add Device wizard by default and may be run at any time from the managed device list.

Re-install policy: is used to perform a quick install of the policy package. It doesn't give the ability to preview the changes that will be installed to the managed device.

NEW QUESTION 39

Examine the output from the BGP real time debug shown in the exhibit, then the answer the question below:

```
# diagnose ip router bgp all enable
# diagnose ip router bgp level info
# diagnose debug enable
"BGP: 10.200.3.1-Outgoing [DECODE] KAlive: Received!"
"BGP: 10.200.3.1-Outgoing [FSM] State: OpenConfirm Event: 26"
"BGP: 10.200.3.1-Outgoing [DECODE] Msg-Hdr: type 2, length 56"
"BGP: 10.200.3.1-Outgoing [DECODE] Update: Starting UPDATE decoding... Byte
(37), msg_size (37)"
"BGP: 10.200.3.1-Outgoing [DECODE] Update: NLRI Len(13)"
"BGP: 10.200.3.1-Outgoing [FSM] State: Established Event: 27"
"BGP: 10.200.3.1-Outgoing [RIB] Update: Received Prefix 0.0.0.0/0"
"BGP: 10.200.3.1-Outgoing [RIB] Update: Received Prefix 10.200.4.0/24"
"BGP: 10.200.3.1-Outgoing [RIB] Update: Received Prefix 10.200.3.0/24"
"BGP: 10.200.3.1-Outgoing [RIB] Update: Received Prefix 10.0.2.0/24"
"BGP: 10.200.3.1-Outgoing [FSM] State: Established Event: 34"
"BGP: 10.200.3.1-Outgoing [ENCODE] Msg-Hdr: Type 2"
"BGP: 10.200.3.1-Outgoing [ENCODE] Attr IP-Unicast: Tot-attr-len 20"
"BGP: 10.200.3.1-Outgoing [ENCODE] Update: Msg #5 Size 55"
"BGP: 10.200.3.1-Outgoing [FSM] State: Established Event: 34"
```

Which statements are true regarding the output in the exhibit? (Choose two.)

- A. BGP peers have successfully interchanged Open and Keepalive messages.
- B. Local BGP peer received a prefix for a default route.
- C. The state of the remote BGP peer is OpenConfirm.
- D. The state of the remote BGP peer will go to Connect after it confirms the received prefixes.

Answer: AB

NEW QUESTION 44

Examine the following partial outputs from two routing debug commands; then answer the question below:

```
#get router info routing-table database
S      0.0.0.0/. [20/0] via 10.200.2.254, port2, [10/0]
S      *> 0.0.0.0/0 [10/0] via 10.200.1.254, port1
# get router info routing-table all
S*     0.0.0.0/0 [10/0] via 10.200.1.254, port1
```

Why the default route using port2 is not displayed in the output of the second command?

- A. It has a lower priority than the default route using port1.
- B. It has a higher priority than the default route using port1.
- C. It has a higher distance than the default route using port1.
- D. It is disabled in the FortiGate configuration.

Answer: C

Explanation:

<http://kb.fortinet.com/kb/viewContent.do?externalId=FD32103>

NEW QUESTION 46

Refer to the exhibits.

```
config vpn ipsec phase1-interface
edit "user-1"
set type dynamic
set interface "port1"
set mode main
set xauthtype auto
set authusrgrp "Users-1"
set peertype any
set dhgrp 14 15 19
set proposal aes128-sha256 aes256-sha384
set psksecret <encrypted_password>
next
```

Which contain the partial configurations of two VPNs on FortiGate.

An administrator has configured two VPNs for two different user groups. Users who are in the Users-2 group are not able to connect to the VPN. After running a diagnostics command, the administrator discovered that FortiGate is not matching the user-2 VPN for members of the Users-2 group.

Which two changes must administrator make to fix the issue? (Choose two.)

- A. Use different pre-shared keys on both VPNs
- B. Enable Mode Config on both VPNs.
- C. Set up specific peer IDs on both VPNs.
- D. Change to aggressive mode on both VPNs.

Answer: CD

NEW QUESTION 50

Examine the following partial output from a sniffer command; then answer the question below.

```
# diagnose sniff packet any 'icmp' 4
interfaces= [any]
filters = [icmp]
2.101199 wan2 in 192.168.1.110-> 4.2.2.2: icmp: echo request
2.101400 wan1 out 172.17.87.16-> 4.2.2.2: icmp: echo request
.....
2.123500 wan2 out 4.2.2.2-> 192.168.1.110: icmp: echo reply
244 packets received by filter
5 packets dropped by kernel
```

What is the meaning of the packets dropped counter at the end of the sniffer?

- A. Number of packets that didn't match the sniffer filter.
- B. Number of total packets dropped by the FortiGate.
- C. Number of packets that matched the sniffer filter and were dropped by the FortiGate.
- D. Number of packets that matched the sniffer filter but could not be captured by the sniffer.

Answer: D

Explanation:

<https://kb.fortinet.com/kb/documentLink.do?externalID=11655>

NEW QUESTION 51

An administrator has configured two FortiGate devices for an HA cluster. While testing HA failover, the administrator notices that some of the switches in the network continue to send traffic to the former primary device. The administrator decides to enable the setting link-failed-signal to fix the problem.

Which statement about this setting is true?

- A. It sends an ARP packet to all connected devices, indicating that the HA virtual MAC address is reachable through a new master after a failover.
- B. It sends a link failed signal to all connected devices.
- C. It disabled all the non-heartbeat interfaces in all HA members for two seconds after a failover.
- D. It forces the former primary device to shut down all its non-heartbeat interfaces for one second, while the failover occurs.

Answer: D

NEW QUESTION 56

View the exhibit, which contains the partial output of an IKE real-time debug, and then answer the question below.


```
ike 0:c49e59846861b0f6/0000000000000000:278: responder: main mode get 1st message...
ike 0:c49e59846861b0f6/0000000000000000:278: incoming proposal:
ike 0:c49e59846861b0f6/0000000000000000:278: proposal id = 0:
ike 0:c49e59846861b0f6/0000000000000000:278:   protocol id = ISAKMP:
ike 0:c49e59846861b0f6/0000000000000000:278:   trans_id = KEY_IKE.
ike 0:c49e59846861b0f6/0000000000000000:278:   encapsulation = IKE/none
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_ENCRYPT_ALG, val=3DES_CBC.
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:c49e59846861b0f6/0000000000000000:278:   type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_GROUP, val=MODP2048.
ike 0:c49e59846861b0f6/0000000000000000:278: ISAKMP SA lifetime=86400
...
ike 0:c49e59846861b0f6/0000000000000000:278: my proposal, gw VPN:
ike 0:c49e59846861b0f6/0000000000000000:278: proposal id = 1:
ike 0:c49e59846861b0f6/0000000000000000:278:   protocol id = ISAKMP:
ike 0:c49e59846861b0f6/0000000000000000:278:   trans_id = KEY_IKE.
ike 0:c49e59846861b0f6/0000000000000000:278:   encapsulation = IKE/none
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_ENCRYPT_ALG, val=AES_CBC,
key-len=256
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:c49e59846861b0f6/0000000000000000:278:   type=AUTH_METHOD, val=PRESHARED_KEY.
ike 0:c49e59846861b0f6/0000000000000000:278:   type=OAKLEY_GROUP, val=MODP2048.
ike 0:c49e59846861b0f6/0000000000000000:278: ISAKMP SA lifetime=86400
...
ike 0:c49e59846861b0f6/0000000000000000:278: negotiation failure
ike Negotiate ISAKMP SA Error: ike 0:c49e59846861b0f6/0000000000000000:278:
proposal chosen
...
```

Why didn't the tunnel come up?

- A. The pre-shared keys do not match.
- B. The remote gateway's phase 2 configuration does not match the local gateway's phase 2 configuration.
- C. The remote gateway's phase 1 configuration does not match the local gateway's phase 1 configuration.
- D. The remote gateway is using aggressive mode and the local gateway is configured to use man mode.

Answer: C

NEW QUESTION 60

An administrator has configured a FortiGate device with two VDOMs: root and internal. The administrator has also created an inter-VDOM link that connects both VDOMs. The objective is to have each VDOM advertise some routes to the other VDOM via OSPF through the inter-VDOM link. What OSPF configuration settings must match in both VDOMs to have the OSPF adjacency successfully forming? (Choose three.)

- A. Router ID.
- B. OSPF interface area.
- C. OSPF interface cost.
- D. OSPF interface MTU.
- E. Interface subnet mask.

Answer: BDE

NEW QUESTION 61

View the exhibit, which contains a partial web filter profile configuration, and then answer the question below.

Name

default

Comments

Default web filtering. 22/255

☒

FortiGuard category based filter

Show ☒ Allow

☒ Bandwidth Consuming

☒ File Sharing and Storage

☒

Status URL Filter

Block invalid URLs ☒

URL Filter ☒

+ Create

Edit

Delete

URL	Type	Action	Status
*dropbox.com	Wildcard	<input checked="" type="checkbox"/> Block	Enable

Web content filter ☒

+ Create new

Edit

Delete

Pattern Type	Pattern	Language	Action	Status
Wildcard	*dropbox*	Western	<input checked="" type="checkbox"/> Exempt	Enable

Which action will FortiGate take if a user attempts to access www.dropbox.com, which is categorized as File Sharing and Storage?

- A. FortiGate will exempt the connection based on the Web Content Filter configuration.
- B. FortiGate will block the connection based on the URL Filter configuration.
- C. FortiGate will allow the connection based on the FortiGuard category based filter configuration.
- D. FortiGate will block the connection as an invalid URL.

Answer: B

Explanation:

fortigate does it in order Static URL -> FortiGuard -> Content -> Advanced (java, cookie removal..)so block it in first step

NEW QUESTION 62

An administrator has configured a dial-up IPsec VPN with one phase 2, extended authentication (XAuth) and IKE mode configuration. The administrator has also enabled the IKE real time debug:

diagnose debug application ike-1 diagnose debug enable

In which order is each step and phase displayed in the debug output each time a new dial-up user is connecting to the VPN?

- A. Phase1; IKE mode configuration; XAuth; phase 2.
- B. Phase1; XAuth; IKE mode configuration; phase2.
- C. Phase1; XAuth; phase 2; IKE mode configuration.
- D. Phase1; IKE mode configuration; phase 2; XAuth.

Answer: B

Explanation:

https://help.fortinet.com/fos50hlp/54/Content/FortiOS/fortigate-ipsecvpn-54/IPsec_VPN_Concepts/IKE_Packet

NEW QUESTION 65

Which statement is true regarding File description (FD) conserve mode?

- A. IPS inspection is affected when FortiGate enters FD conserve mode.
- B. A FortiGate enters FD conserve mode when the amount of available description is less than 5%.
- C. FD conserve mode affects all daemons running on the device.
- D. Restarting the WAD process is required to leave FD conserve mode.

Answer: B

NEW QUESTION 69

Examine the output of the 'get router info ospf neighbor' command shown in the exhibit; then answer the question below.

```
# get router info ospf neighbor
```

```
OSPF process 0:
```

Neighbor ID	Pri	State	Dead Time	Address	Interface
0.0.0.69	1	Full/DR	00:00:32	10.126.0.69	wan1
0.0.0.117	1	Full/DROther	00:00:34	10.126.0.117	wan1
0.0.0.2	1	Full/-	00:00:36	172.16.1.2	ToRemote

Which statements are true regarding the output in the exhibit? (Choose two.) Refer to the exhibit, which shows the output of a debug command. Which statement about the output is true?

- A. The OSPF routers with the IDs 0.0.0.69 and 0.0.0.117 are both designated routers for the wan1 network.
- B. I network.
- C. The OSPF router with the ID 0.0.0.2 is the designated router for the ToRemote network.
- D. The local FortiGate is the designated router for the wan1 network.
- E. The interface ToRemote is a point-to-point OSPF network.

Answer: D

Explanation:

<https://www.cisco.com/c/en/us/support/docs/ip/open-shortest-path-first-ospf/13685-13.html>

NEW QUESTION 74

The CLI command set intelligent-mode <enable | disable> controls the IPS engine's adaptive scanning behavior. Which of the following statements describes IPS adaptive scanning?

- A. Determines the optimal number of IPS engines required based on system load.
- B. Downloads signatures on demand from FDS based on scanning requirements.
- C. Determines when it is secure enough to stop scanning session traffic.
- D. Choose a matching algorithm based on available memory and the type of inspection being performed.

Answer: C

Explanation:

Configuring IPS intelligenceStarting with FortiOS 5.2, intelligent-mode is a new adaptive detection method. This command is enabled the default and it means that the IPS engine will perform adaptive scanning so that, for some traffic, the FortiGate can quickly finish scanning and offload the traffic to NPU or kernel. It is a balanced method which could cover all known exploits. When disabled, the IPS engine scans every single byte.

```
config ips globalset intelligent-mode {enable|disable}end
```

NEW QUESTION 75

Examine the output of the 'diagnose debug rating' command shown in the exhibit; then answer the question below.

```
# diagnose debug rating
Locale      : english
License     : Contract
Expiration  : Wed Mar 27 17:00:00 20xx
== Server List (Mon Apr 16 15:32:55 20xx) ==
```

IP	Weight	RTT	Flags	TZ	Packets	Curr Lost	Total Lost
69.195.205.101	10	45		-5	262432	0	846
69.195.205.102	10	46		-5	329072	0	6806
209.222.147.43	10	75		-5	71638	0	275
96.45.33.65	20	71		-8	36875	0	92
208.91.112.196	20	103	DI	-8	34784	0	1070
208.91.112.198	20	107	D	-8	35170	0	1533
80.85.69.41	60	144		0	33728	0	120
62.209.40.73	71	226		1	33797	0	192
121.111.236.180	150	197		9	33754	0	145
69.195.205.103	45	44	F	-5	26410	26226	26227

Which statement are true regarding the output in the exhibit? (Choose two.)

- A. There are three FortiGuard servers that are not responding to the queries sent by the FortiGate.
- B. The TZ value represents the delta between each FortiGuard server's time zone and the FortiGate's time zone.
- C. FortiGate will send the FortiGuard queries to the server with highest weight.
- D. A server's round trip delay (RTT) is not used to calculate its weight.

Answer: BC

NEW QUESTION 77

Which of the following statements are true regarding the SIP session helper and the SIP application layer gateway (ALG)? (Choose three.)

- A. SIP session helper runs in the kernel; SIP ALG runs as a user space process.
- B. SIP ALG supports SIP HA failover; SIP helper does not.
- C. SIP ALG supports SIP over IPv6; SIP helper does not.
- D. SIP ALG can create expected sessions for media traffic; SIP helper does not.
- E. SIP helper supports SIP over TCP and UDP; SIP ALG supports only SIP over UDP.

Answer: BCD

NEW QUESTION 78

When does a RADIUS server send an Access-Challenge packet?

- A. The server does not have the user credentials yet.
- B. The server requires more information from the user, such as the token code for two-factor authentication.
- C. The user credentials are wrong.
- D. The user account is not found in the server.

Answer: B

NEW QUESTION 82

Examine the partial output from two web filter debug commands; then answer the question below:

```
# diagnose test application urlfilter 3
Domain | IP      DB Ver  T URL
34000000| 34000000  16.40224 P Bhttp://www.fgt99.com/

# get webfilter categories
g07 General Interest - Business:
  34 Finance and Banking
  37 Search Engines and Portals
  43 General Organizations
  49 Business
  50 Information and Computer Security
  51 Government and Legal Organizations
  52 Information Technology
```

Based on the above outputs, which is the FortiGuard web filter category for the web site www.fgt99.com?

- A. Finance and banking
- B. General organization.
- C. Business.
- D. Information technology.

Answer: C

NEW QUESTION 83

Which configuration can be used to reduce the number of BGP sessions in an IBGP network?

- A. Neighbor range

- B. Route reflector
- C. Next-hop-self
- D. Neighbor group

Answer: B

Explanation:

Route reflectors help to reduce the number of IBGP sessions inside an AS. A route reflector forwards the routers learned from one peer to the other peers. If you configure route reflectors, you don't need to create a full mesh IBGP network. All clients in a cluster only talk to route reflector to get sync routing updates. Route reflectors pass the routing updates to other route reflectors and border routers within the AS.

NEW QUESTION 84

View the exhibit, which contains the output of a diagnose command, and then answer the question below.

```
# diagnose debug rating
Locale      : English
License     : Contract
Expiration  : Thu Sep 28 17:00:00 20XX
-- Server List (Thu APR 19 10:41:32 20XX) --
```

IP	Weight	RTT	Flags	TZ	Packets	Curr Lost	Total Lost
64.26.151.37	10	45		-5	262432	0	846
64.26.151.35	10	46		-5	329072	0	6806
66.117.56.37	10	75		-5	71638	0	275
66.210.95.240	20	71		-8	36875	0	92
209.222.147.36	20	103	DI	-8	34784	0	1070
208.91.112.194	20	107	D	-8	35170	0	1533
96.45.33.65	60	144		0	33728	0	120
80.85.69.41	71	226		1	33797	0	192
62.209.40.74	150	97		9	33754	0	145
121.111.236.179	45	44	F	-5	26410	26226	26227

Which statements are true regarding the Weight value?

- A. Its initial value is calculated based on the round trip delay (RTT).
- B. Its initial value is statically set to 10.
- C. Its value is incremented with each packet lost.
- D. It determines which FortiGuard server is used for license validation.

Answer: C

NEW QUESTION 87

View the global IPS configuration, and then answer the question below.

```
config ips global
    set fail-open disable
    set intelligent-mode disable
    set engine-count 0
    set algorithm engine-pick
end
```

Which of the following statements is true regarding this configuration?

- A. IPS will scan every byte in every session.
- B. FortiGate will spawn IPS engine instances based on the system load.
- C. New packets will be passed through without inspection if the IPS socket buffer runs out of memory.
- D. IPS will use the faster matching algorithm which is only available for units with more than 4 GB memory.

Answer: A

NEW QUESTION 91

View the exhibit, which contains the partial output of an IKE real-time debug, and then answer the question below.

```
ike 0: comes 10.0.0.2:500-> 10.0.0.1:500, ifindex=7...
ike 0: IKEv1 exchange-Aggressive id-baf47d0988e9237f/2f405ef3952f6fda len 430
ike 0: in
BAF47D0988E9237F2F405EF3952F6FDA011004000000000000001AE0400003C0000000100000001000000300101000
ike 0: RemoteSite:4: initiator: aggressive mode get 1st response
ike 0: RemoteSite:4: VID RPC 3947 4A131C81070358455C5728F20E95452F
ike 0: RemoteSite:4: VID DPD APCAD71368A1F1c96B8696FC77570100
ike 0: RemoteSite:4: VID PORTIGATE 8299031757A36082C6A621DE000502D7
ike 0: RemoteSite:4: peer is FortiGate/FortiOS (v6 b932)
ike 0: RemoteSite:4: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3
ike 0: RemoteSite:4: VID FRAGMENTATION 4048B7D56EBCE88525E7DE7F00D6C2D3C0000000
ike 0: RemoteSite:4: received peer identifier FQDN 'remote'
ike 0: RemoteSite:4: negotiation result
ike 0: RemoteSite:4: proposal id = 1:
ike 0: RemoteSite:4:   protocol id - ISAKMP:
ike 0: RemoteSite:4:   trans_id - KEY_IKE.
ike 0: RemoteSite:4:   encapsulation - IKE/none
ike 0: RemoteSite:4:   type-OAKLEY_ENCRYPT_ALG, val-AES_CBC, key-len=128
ike 0: RemoteSite:4:   type-OAKLEY_HASH_ALG, val-SHA
ike 0: RemoteSite:4:   type-AUTH_METHOD, val-PRESHARED_KEY.
ike 0: RemoteSite:4:   type-OAKLEY_GROUP, val-MODP1024.
ike 0: RemoteSite:4: ISAKMP SA lifetime=86400
ike 0: RemoteSite:4: ISAKMP SA baf47d0988e9237f/2f405ef3952f6fda key
16:B25B6C9384D8BDB24E3DA3DC90CF5E73
ike 0: RemoteSite:4: PSK authentication succeeded
ike 0: RemoteSite:4: authentication OK
ike 0: RemoteSite:4: add INITIAL-CONTACT
ike 0: RemoteSite:4: enc
BAF47D0988E9237F2F405EF3952F6FDA081004010000000000000080140000181F2E48BFD8E9D603F
ike 0: RemoteSite:4: out
BAF47D0988E9237F2F405EF3952F6FDA08100401000000000000008c2E3FC9BA061816A396F009A12
ike 0: RemoteSite:4: sent IKE msg (agg_12send) : 10.0.0.1:500 ->10.0.0.2:500, len=140, id-
baf47d0988e9237f/2
ike 0: RemoteSite:4: established IKE SA baf47d0988e9237f/2f405ef3952f6fda
```

Which statements about this debug output are correct? (Choose two.)

- A. The remote gateway IP address is 10.0.0.1.
- B. It shows a phase 1 negotiation.
- C. The negotiation is using AES128 encryption with CBC hash.
- D. The initiator has provided remote as its IPsec peer ID.

Answer: BD

NEW QUESTION 96

Examine the following routing table and BGP configuration; then answer the question below.

```
#get router info routing-table all
*0.0.0.0/0 [10/0] via 10.200.1.254, port1
C10.200.1.0/24 is directly connected, port1
S192.168.0.0/16 [10/0] via 10.200.1.254, port1
# show router bgp
config router bgp
set as 65500
set router-id 10.200.1.1
set network-import-check enable
set ebgp-multipath disable
config neighbor
edit "10.200.3.1"
set remote-as 65501
next
end
config network
edit1
```

The BGP connection is up, but the local peer is NOT advertising the prefix 192.168.1.0/24. Which configuration change will make the local peer advertise this prefix?

- A. Enable the redistribution of connected routers into BGP.
- B. Enable the redistribution of static routers into BGP.
- C. Disable the setting network-import-check.
- D. Enable the setting ebgp-multipath.

Answer: C

NEW QUESTION 101

In which two states is a given session categorized as ephemeral? (Choose two.)

- A. A TCP session waiting to complete the three-way handshake.
- B. A TCP session waiting for FIN ACK.
- C. A UDP session with packets sent and received.
- D. A UDP session with only one packet received.

Answer: AD

NEW QUESTION 105

Which two statements about OCVPN are true? (Choose two.)

- A. Only root vdom supports OCVPN.
- B. OCVPN supports static and dynamic IPs in WAN interface.
- C. OCVPN offers only Hub-Spoke VPNs.
- D. FortiGate devices under different FortiCare accounts can be used to form OCVPN.

Answer: AB

NEW QUESTION 106

What configuration changes can reduce the memory utilization in a FortiGate? (Choose two.)

- A. Reduce the session time to live.
- B. Increase the TCP session timers.
- C. Increase the FortiGuard cache time to live.
- D. Reduce the maximum file size to inspect.

Answer: AD

NEW QUESTION 108

An administrator has configured two FortiGate devices for an HA cluster. While testing the HA failover, the administrator noticed that some of the switches in the network continue to send traffic to the former primary unit. The administrator decides to enable the setting link-failed-signal to fix the problem. Which statement is correct regarding this command?

- A. Forces the former primary device to shut down all its non-heartbeat interfaces for one second while the failover occurs.
- B. Sends an ARP packet to all connected devices, indicating that the HA virtual MAC address is reachable through a new master after a failover.
- C. Sends a link failed signal to all connected devices.
- D. Disables all the non-heartbeat interfaces in all the HA members for two seconds after a failover.

Answer: A

NEW QUESTION 112

View the exhibit, which contains the output of a BGP debug command, and then answer the question below.

```
FGT # get router info bgp summary
BGP router identifier 0.0.0.117, local AS number 65117
BGP table version is 104
3 BGP AS-PATH entries
0 BGP community entries

Neighbor      V    AS  MsgRcvd  MsgSent  TblVer   InQ  OutQ   Up/Down    State/PfxRcd
10.125.0.60    4  65060   1698     1756    103     0     0    03:02:49        1
10.127.0.75    4  65075   2206     2250    102     0     0    02:45:55        1
100.64.3.1     4  65501    101      115      0      0     0         never        Active

Total number of neighbors 3
```

Which of the following statements about the exhibit are true? (Choose two.)

- A. The local router's BGP state is Established with the 10.125.0.60 peer.
- B. Since the counters were last reset; the 10.200.3.1 peer has never been down.
- C. The local router has received a total of three BGP prefixes from all peers.
- D. The local router has not established a TCP session with 100.64.3.1.

Answer: AD

NEW QUESTION 115

Refer to the exhibit, which shows a partial routing table.

```
FGT # get router info routing-table all
...
Routing table for VRF=7
C      10.73.9.0/24 is directly connected, port2

Routing table for VRF=12
C      10.1.0.0/24 is directly connected, port3
S      10.10.4.0/24 [10/0] via 10.1.0.100, port3
C      10.64.1.0/24 is directly connected, port1

Routing table for VRF=21
S      10.1.0.0/24 [10/0] via 10.72.3.254, port4
C      10.72.3.0/24 is directly connected, port4
```

Assuming all the appropriate firewall policies are configured, which two pings will FortiGate route? (Choose two.)

- A. Source IP address: 10.1.0.10. Destination IP address: 10.64.1.52
- B. Source IP address: 10.72.3.52. Destination IP address: 10.1.0.254
- C. Source IP address: 10.10.4.24, Destination IP address: 10.72.3.20
- D. Source IP address: 10.73.9.10, Destination IP address: 10.72.3.15

Answer: AB

NEW QUESTION 117

View the exhibit, which contains the output of a diagnose command, and then answer the question below.

```
diagnose sys session list expectation

session info: proto=6 proto_state=00 duration=3 expire=26 timeout=3600 flags=00000000
sockflag=00000000 sockport=0 av_idx=0 use=3
origin-shaper=
reply-shaper=
ha_id=0 policy_dir=1 tunnel=/
state=new complex
statistic(bytes/packets/allow_err): org=0/0/0 reply=0/0/0 tuples=2
origin->sink: org pre->post, reply pre->post dev=2->4/4->2 gwy=10.0.1.10/10.200.1.254
hook=pre dir-org act=dnat 10.171.121.38:0->10.200.1.1:60426(10.0.1.10:50365)
hook-pre dir-org act=noop 0.0.0.0:0->0.0.0.0:0(0.0.0.0:0)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=000000e9 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

What statements are correct regarding the output? (Choose two.)

- A. This is an expected session created by a session helper.
- B. Traffic in the original direction (coming from the IP address 10.171.122.38) will be routed to the next-hop IP address 10.0.1.10.
- C. Traffic in the original direction (coming from the IP address 10.171.122.38) will be routed to the next-hop IP address 10.200.1.1.
- D. This is an expected session created by an application control profile.

Answer: AC

NEW QUESTION 121

An administrator added the following Ipsec VPN to a FortiGate configuration:

```
config vpn ipsec phase1-interface edit "RemoteSite"
set type dynamic
set interface "port1" set mode main
set psksecret ENC LCVkCiK2E2PhVUzZe next
end
config vpn ipsec phase2-interface edit "RemoteSite"
set phase1 name "RemoteSite" set proposal 3des-sha256
next end
```

However, the phase 1 negotiation is failing. The administrator executed the IKF real time debug while attempting the Ipsec connection. The output is shown in the exhibit.

```
ike 0: comes 10.200.3.1:500->10.200.1.1:500, ifindex=2....
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=716
ike 0:xxx/xxx:16: responder: main mode get 1st message...
ike 0:xxx/xxx:16: VID RFC 3947 4A131C81070358455C5728F20E95452F
...
ike 0:xxx/xxx:16: negotiation result
ike 0:xxx/xxx:16: proposal id = 1:
ike 0:xxx/xxx:16: protocol id = ISAKMP:
ike 0:xxx/xxx:16: trans_id = KEY IKE.
ike 0:xxx/xxx:16: encapsulation = IKE/none
ike 0:xxx/xxx:16: type=OAKLEY_ENCRYPT_ALG, val=AES_CBC.
ike 0:xxx/xxx:16: type=OAKLEY_HASH_ALG, val=SHA2_256.
ike 0:xxx/xxx:16: type=AUTH_METHOD, val=PRE_SHARED_KEY.
ike 0:xxx/xxx:16: type=OAKLEY_GROUP, val=MODP2048.
ike 0:xxx/xxx:16: ISAKMP SA lifetime=86400
ike 0:xxx/xxx:16: SA proposal chosen, matched gateway DialUpUsers
...
ike 0:DialUpUsers:16: sent IKE msg (ident_r1send): 10.200.1.1:500->10.200.3.1:500, len
id=xxx/xxx
ike 0: comes 10.200.3.1:500->10.200.1.1:500, ifindex=2....
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=380
ike 0:DialUpUsers:16: responder: main mode get 2nd message...
ike 0:DialUpUsers:16: NAT not detected
ike 0:DialUpUsers:16: sent IKE msg (ident_r2send): 10.200.1.1:500->10.200.3.1:500, len
id=xxx/xxx
ike 0:DialUpUsers:16: ISAKMP SA xxx/xxx key 16:3D33E2EF00BE927701B5C25B05A62415
ike 0: comes 10.200.3.1:500->10.200.1.1:500, ifindex=2....
ike 0: IKEv1 exchange=Identity Protection id=xxx/xxx len=108
ike 0:DialUpUsers:16: responder: main mode get 3rd message...
ike 0:DialUpUsers:16: probable pre-shared secret mismatch
ike 0:DialUpUsers:16: unable to parse msg
```

What is causing the IPsec problem in the phase 1 ?

- A. The incoming IPsec connection is matching the wrong VPN configuration
- B. The phrase-1 mode must be changed to aggressive
- C. The pre-shared key is wrong
- D. NAT-T settings do not match

Answer: C

NEW QUESTION 126

View these partial outputs from two routing debug commands:

```
# get router info kernel
tab=254 vf=0 scope=0 type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.1.254
dev=2(port1)
tab=254 vf=0 scope=0 type=1 proto=11 prio=0 0.0.0.0/0.0.0.0/0->0.0.0.0/0 pref=0.0.0.0 gwy=10.200.2.254
dev=3(port2)
tab=254 vf=0 scope=253 type=1 proto=2 prio=0 0.0.0.0/0.0.0.0/0->10.0.1.0/24 pref=10.0.1.254 gwy=0.0.0.0
dev=4(port3)
# get router info routing-table all
S* 0.0.0.0/0 [10/0] via 10.200.1.254, port1
    [10/0] via 10.200.2.254, port2, [10/0]
C 10.0.1.0/24 is directly connected, port3
C 10.200.1.0/24 is directly connected, port1
C 10.200.2.0/24 is directly connected, port2
```

Which outbound interface will FortiGate use to route web traffic from internal users to the Internet?

- A. Both port1 and port2
- B. port3
- C. port1
- D. port2

Answer: C

NEW QUESTION 127

Which two statements about FortiManager is true when it is deployed as a local FDS? (Choose two.)

- A. It caches available firmware updates for unmanaged devices.
- B. It can be configured as an update server, or a rating server, but not both.
- C. It supports rating requests from both managed and unmanaged devices.
- D. It provides VM license validation services.

Answer: CD

NEW QUESTION 130

What is the diagnose test application ipsmonitor 99 command used for?

- A. To enable IPS bypass mode
- B. To provide information regarding IPS sessions
- C. To disable the IPS engine
- D. To restart all IPS engines and monitors

Answer: D

NEW QUESTION 134

Examine the output of the 'get router info bgp summary' command shown in the exhibit; then answer the question below.

```
# get router info bgp summary
BGP router identifier 0.0.0.117, local AS number 65117
BGP table version is 104
3 BGP AS-PATH entries
0 BGP community entries

Neighbor    V    AS  MsgRcvd  MsgSent  TblVer  InQ  OutQ  Up/Down  State/PfxRcd
10.125.0.60  4   65060   1698      1756    103   0     0  03:02:49        1
10.127.0.75  4   65075   2206      2250    102   0     0  02:45:55        1
10.200.3.1   4   65501    101        115     0    0     0    never        Active

Total number of neighbors 3
```

Which statements are true regarding the output in the exhibit? (Choose two.)

- A. BGP state of the peer 10.125.0.60 is Established.
- B. BGP peer 10.200.3.1 has never been down since the BGP counters were cleared.
- C. Local BGP peer has not received an OpenConfirm from 10.200.3.1.
- D. The local BGP peer has received a total of 3 BGP prefixes.

Answer: AC

NEW QUESTION 139

Refer to the exhibit, which contains the partial output of a diagnose command.


```
Spoke-2 # dia vpn tunnel list
list all ipsec tunnel in vd 0
-----
name=VPN ver=1 serial=1 10.200.5.1:0 -> 10.200.4.1:0
bound_if=3 lgwy=statistic/1 tun=intf/0 mode=auto/1 encap=none/0
proxyid_num=1 child_num=0 refernt=15 ilast=10 olast=792 auto-discovery=0
stat: rxp=0 txp=0 rxb=0 txb=0
dpd: mode=on-demand on=1 idle=20000ms retry=3 count=0 seqno=0
natt: mode=none draft=0 interval=0 remote_port=0
proxyid=VPN proto=0 sa=1 ref=2 serial=1
src: 0:10.1.2.0/255.255.255.0:0
dat: 0:10.1.1.0/255.255.255.0:0
SA: ref=3 options=2e type=00 soft=0 mtu=1438 expire=42403/OB replaywin=204B seqno=1
esn=replaywin_lastseq=00000000
life: type=01 bytes=0/0 timeout=43177/43200
dec: spi=ccclf66d esp=aes key=16 280e5cd6f9bacc65ac771556c464ffbd
ah=shal key=20 c68091d68753578785de6a7a6b276b506e527
```

Based on the output, which two statements are correct? (Choose two.)

- A. Anti-replay is enabled.
- B. DPD is disabled.
- C. Remote gateway IP is 10.200.4.1.
- D. Quick mode selectors are disabled.

Answer: AC

NEW QUESTION 141

View the following FortiGate configuration.

```
config system global
    set snat-route-change disable
end
config router static
    edit 1
        set gateway 10.200.1.254
        set priority 5
        set device "port1"
    next
    edit 2
        set gateway 10.200.2.254
        set priority 10
        set device "port2"
    next
end
```

All traffic to the Internet currently egresses from port1. The exhibit shows partial session information for Internet traffic from a user on the internal network:

```
# diagnose sys session list
session info: proto=6 proto_state=01 duration=17 expire=7 timeout=3600
flags=00000000 sockflag=00000000 sockport=0 av_idx=0 use=3
ha_id=0 policy_dir=0 tunnel=/
state=may_dirty none app_ntf
statistic(bytes/packets/allow_err): org=57555/7/1 reply=23367/19/1 tuples=2
orgin->sink: org pre->post, reply pre->post dev=4->2/2->4
gwy=10.200.1.254/10.0.1.10
hook=post dir=org act=snat 10.0.1.10:64907->54.239.158.170:80(10.200.1.1:64907)
hook=pre dir=reply act=dnat 54.239.158.170:80->10.200.1.1:64907(10.0.1.10:64907)
pos/(before, after) 0/(0,0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=00000294 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

If the priority on route ID 1 were changed from 5 to 20, what would happen to traffic matching that user's session?

- A. The session would remain in the session table, and its traffic would still egress from port1.
- B. The session would remain in the session table, but its traffic would now egress from both port1 and port2.
- C. The session would remain in the session table, and its traffic would start to egress from port2.
- D. The session would be deleted, so the client would need to start a new session.

Answer: A

Explanation:

<http://kb.fortinet.com/kb/documentLink.do?externalID=FD40943>

NEW QUESTION 146

Four FortiGate devices configured for OSPF connected to the same broadcast domain. The first unit is elected as the designated router The second unit is elected as the backup designated router Under normal operation, how many OSPF full adjacencies are formed to each of the other two units?

- A. 1
- B. 2
- C. 3
- D. 4

Answer: B

NEW QUESTION 151

View the exhibit, which contains the output of diagnose sys session list, and then answer the question below.

```
# diagnose sys session list
session info: proto=6 proto_state=01 duration=73 expire=3597 timeout=3600
flags=00000000 sockflag=00000000 sockport=0 av_idx=0 use=3
origin-shaper=
reply-shaper=
per_ip_shaper=
ha_id=0 policy_dir=0 tunnel=/
state=may_dirty synced none app_ntf
statistic (bytes/packets/allow_err): org=822/11/1 reply=9037/15/1 tuples=2
origin->sink: org pre->post, reply pre->post dev=4->2/2->4 gwy=10.200.1.254/10.0.1.10
hook=post dir=org act=snst 10.0.1.10:65464->54.192.15.182:80(10.200.1.1:65464
hook-pre dir=reply act=dnat 54.192.15.182:80->10.200.1.1:65464(10.0.1.10:65464)
pos/ (before, after) 0/(0/0), 0/(0,0)
misc=0 policy_id=1 auth_info=0 chk_client_info=0 vd=0
serial=000000098 tos=ff/ff ips_view=0 app_list=0 app=0
dd_type=0 dd_mode=0
```

If the HA ID for the primary unit is zero (0), which statement is correct regarding the output?

- A. This session is for HA heartbeat traffic.
- B. This session is synced with the slave unit.
- C. The inspection of this session has been offloaded to the slave unit.
- D. This session cannot be synced with the slave unit.

Answer: B

NEW QUESTION 155

.....

Thank You for Trying Our Product

We offer two products:

1st - We have Practice Tests Software with Actual Exam Questions

2nd - Questions and Answers in PDF Format

NSE7_EFW-7.0 Practice Exam Features:

- * NSE7_EFW-7.0 Questions and Answers Updated Frequently
- * NSE7_EFW-7.0 Practice Questions Verified by Expert Senior Certified Staff
- * NSE7_EFW-7.0 Most Realistic Questions that Guarantee you a Pass on Your FirstTry
- * NSE7_EFW-7.0 Practice Test Questions in Multiple Choice Formats and Updatesfor 1 Year

100% Actual & Verified — Instant Download, Please Click
[Order The NSE7_EFW-7.0 Practice Test Here](#)